



1 KITCHEN POWER ELECTRICAL PLAN
1/4"=1'-0"

KITCHEN EQUIPMENT SCHEDULE																	
PLAN MARK	EQUIPMENT DESCRIPTION/CATALOG NO.	LOCATION	MECHANICAL DATA					ELECTRICAL DATA						NOTES			
			VOLTS	PHASE	MOTOR HP	HLA FLA	HEAT KW	AMPS	MCA	DEVICE TYPE	HEIGHT	MAX BRKR	IPANEL FUSE		ISERVED FROM	CIRCUIT	WIRES
1	WARMER	KITCHEN	120	1		16.0	2	16.0	20	5-20R	18"	20	A	1	2 #10, 1 #10G	10.75	
1	WARMER	KITCHEN	120	1		16.0	2	16.0	20	5-20R	18"	20	A	3	2 #10, 1 #10G	10.75	
1	WARMER	KITCHEN	120	1		16.0	2	16.0	20	5-20R	18"	20	A	5	2 #10, 1 #10G	10.75	
1	WARMER	KITCHEN	120	1		16.0	2	16.0	20	5-20R	18"	20	A	7	2 #10, 1 #10G	10.75	
	KITCHEN DUPLEX	KITCHEN	120	1		10.0	1	10.0	13	5-20R	18"	20	A	9	2 #10, 1 #10G	10.75	
	KITCHEN DUPLEX	KITCHEN	120	1		10.0	1	10.0	13	5-20R	18"	20	A	11	2 #10, 1 #10G	10.75	
2	STEAMER	KITCHEN	208	1		14.4	3	14.4	18	FWR	18"	20	A	13/15	2 #10, 1 #10G	10.75	FWR
	KITCHEN DUPLEX	KITCHEN	120	1		10.0	1	10.0	13	5-20R	18"	20	A	17	2 #10, 1 #10G	10.75	
3	KITCHEN DUPLEX	KITCHEN	120	1		10.0	1	10.0	13	5-20R	34"	20	A	19	2 #10, 1 #10G	10.75	BTC
3	KITCHEN DUPLEX	KITCHEN	120	1		10.0	1	10.0	13	5-20R	34"	20	A	21	2 #10, 1 #10G	10.75	BTC
12	ROLL WARMER	KITCHEN	120	1		7.5	1	7.5	9	5-20R	18"	20	A	23	2 #10, 1 #10G	10.75	
13	CASH DRAWER	KITCHEN	120	1		5.0	1	5.0	6	5-20R	24"	20	A	25	2 #10, 1 #10G	10.75	BTC
	KITCHEN DUPLEX	KITCHEN	120	1		10.0	1	10.0	13	5-20R	34"	20	A	27	2 #10, 1 #10G	10.75	BTC
3	KITCHEN DUPLEX	KITCHEN	120	1		10.0	1	10.0	13	5-20R	34"	20	A	29	2 #10, 1 #10G	10.75	BTC
13	CASH DRAWER	KITCHEN	120	1		5.0	1	5.0	6	5-20R	24"	20	A	31	2 #10, 1 #10G	10.75	BTC
12	ROLL WARMER	KITCHEN	120	1		7.5	1	7.5	9	5-20R	18"	20	A	33	2 #10, 1 #10G	10.75	ALT. LDC.
3	KITCHEN DUPLEX	KITCHEN	120	1		10.0	1	10.0	13	5-20R	34"	20	A	35	2 #10, 1 #10G	10.75	BTC
3	KITCHEN DUPLEX	KITCHEN	120	1		10.0	1	10.0	13	5-20R	34"	20	A	37	2 #10, 1 #10G	10.75	BTC
	KITCHEN DUPLEX	KITCHEN	120	1		10.0	1	10.0	13	5-20R	18"	20	A	39	2 #10, 1 #10G	10.75	
	KITCHEN DUPLEX	KITCHEN	120	1		10.0	1	10.0	13	5-20R	18"	20	A	41	2 #10, 1 #10G	10.75	
8	WALKIN REFER	KITCHEN	120	1		10.6	1	10.6	13	5-20R	87"	20	A	2	2 #10, 1 #10G	10.75	
7	ROLL IN REFER	KITCHEN	120	1		8.0	1	8.0	10	5-20R	87"	20	A	4	2 #10, 1 #10G	10.75	
17	COFFEE	KITCHEN	208	1		29.0	6	29.0	36	1L6-40R	24"	40	A	6/8	4 #8, 1 #10G	10.75	FWR
4	ICE MAKER	KITCHEN	208	1		11.0	2	11.0	14	J-BOX	60"	20	A	10/12	4 #10, 1 #10G	10.75	BTC
	KITCHEN DUPLEX	KITCHEN	120	1		10.0	1	10.0	13	5-20R	18"	20	A	14	2 #10, 1 #10G	10.75	

- MEP SUB-CONTRACTORS ARE RESPONSIBLE FOR COORDINATION WITH ARCHITECTURAL PLANS FOR ALL WORK. REFERENCE GENERAL ELECTRICAL NOTE G7/E3.0.
- REFERENCE ELECTRICAL NOTES AND DETAILS AND OTHER ELECTRICAL PLANS FOR ADDITIONAL POWER REQUIREMENTS.
- REFERENCE KITCHEN PLANS FOR EQUIPMENT INFORMATION. REFERENCE ARCHITECTURAL DRAWINGS AND SPECIFICATIONS FOR EQUIPMENT LOCATIONS.
- COORDINATE DEVICE LOCATIONS IN FIELD WITH ARCHITECT.
- REFERENCE PANEL BOARD SCHEDULES FOR ADDITIONAL LOAD AND CIRCUIT INFORMATION.
- REFERENCE MECHANICAL PLANS AND SPECIFICATIONS FOR MECHANICAL AND PLUMBING EQUIPMENT REQUIREMENTS.
- REFERENCE MECHANICAL AND ARCHITECTURAL PLANS FOR MECHANICAL AND PLUMBING EQUIPMENT LOCATIONS.